



Features:

- **Mixer/Power Amplifier**
- **3 Inputs:**
 - 1 x mic/line (balanced Euroblock)
 - 2 x line/stereo (bal Euroblock, unbal stereo)
- **Independent Input Gain**
- **Priority Mute**
- **Signal Presence LEDs**
- **Zone 2 Output for Selected inputs**
- **Bass & Treble Controls**
- **60W Output:**
 - 4 Ohms (direct out)
 - 25V Transformer Isolated (US)
 - 70V Transformer Isolated
 - 100V Transformer Isolated (EC, Japan)
- **Power Saving Mode**
 - manual or automatic
- **120VAC model**
 - (USA & Canada and Associated)
- **230VAC model**
 - (EC and Associated)
- **Optional Rack Kit**
 - part number : RMK-360
- **5 Year Warranty**

Ashly now has the tools for creating and controlling a simple sound system for a 'convenience' gas & grocery store. This application uses the **TM-360**, a mixer/power amplifier with 60W output. Features include three inputs with input gain control and signal presence LEDs, priority mute, and an input assignable 'Zone 2' output (1W + line level) for extra coverage.

Connected to Input 1 of the **TM-360** is a paging microphone with a push-to-talk bar (switch). Background music is connected to Input 2. The background music will play at the pumps and in the retail area. Pushing the talk bar and speaking into the microphone will automatically mute the background music (Mix Configuration SW4 'ON'). The paging microphone will be heard at the pumps but is not routed to retail area. Only the background music is routed to Zone 2 (Mix Configuration SW2 'ON')."

60W-70V from the TM-360 is connected to the paging horns in the gas pump area. A 400Hz high-pass filter is engaged to protect the paging horns (Mix Configuration SW7 'ON'). The paging horns can be tapped at a maximum of 15W.

The Zone 2 output (1W) is connected in 'series' to 8 ohm ceiling speakers in the retail area. Each ceiling speaker will have approximately 1/4W available.

To save energy, after 25 minutes with no input, the mixer/power amplifier will automatically go to standby until further audio signal is applied.

Visit www.ashly.com to download Ashly data sheets and manuals